


## BUSH FOR JIC

BUSSOLA  
JUPE  
ROHRANSCHLUSS FÜR JIC-MUTTER  
CASQUILLO



| Code         | Thread | Dimensions       |             |             | Pressure   |             |
|--------------|--------|------------------|-------------|-------------|------------|-------------|
|              |        | Ø                | D<br>mm     | L1<br>mm    | PN<br>Bar  | Psi         |
| ABJ06        |        | 6 - 1/4"         | 9.7         | 10.4        | 345        | 5003        |
| <b>ABJ08</b> |        | <b>8 - 5/16"</b> | <b>11.3</b> | <b>11.2</b> | <b>345</b> | <b>5003</b> |
| ABJ3/8"      |        | 3/8"             | 12.7        | 12.7        | 345        | 5003        |
| <b>ABJ10</b> |        | <b>10</b>        | <b>12.7</b> | <b>12.7</b> | <b>345</b> | <b>5003</b> |
| ABJ1/2"      |        | 1/2"             | 17.3        | 14.2        | 310        | 4495        |
| <b>ABJ12</b> |        | <b>12</b>        | <b>17.3</b> | <b>14.2</b> | <b>310</b> | <b>4495</b> |
| ABJ14        |        | 14               | 20.2        | 16.8        | 240        | 3480        |
| <b>ABJ15</b> |        | <b>15</b>        | <b>20.2</b> | <b>16.8</b> | <b>240</b> | <b>3480</b> |
| ABJ16        |        | 16 - 5/8"        | 20.2        | 16.8        | 240        | 3480        |
| <b>ABJ18</b> |        | <b>18</b>        | <b>24.6</b> | <b>17.3</b> | <b>240</b> | <b>3480</b> |
| ABJ20        |        | 20 - 3/4"        | 24.6        | 17.3        | 210        | 3045        |
| <b>ABJ22</b> |        | <b>22</b>        | <b>31</b>   | <b>19.8</b> | <b>210</b> | <b>3045</b> |
| ABJ25        |        | 25 - 1"          | 31          | 19.8        | 210        | 3045        |
| <b>ABJ30</b> |        | <b>30</b>        | <b>38.9</b> | <b>23.1</b> | <b>170</b> | <b>2465</b> |
| ABJ32        |        | 32 1.1/4"        | 38.9        | 23.1        | 170        | 2465        |
| <b>ABJ38</b> |        | <b>38 1.1/2"</b> | <b>45.3</b> | <b>28.4</b> | <b>140</b> | <b>2030</b> |